



908

Stereo Amplifier & Switcher (40 Watts per Channel)

| Speakers | Ethernet - RJ-45



The 908 is a high-performance audio amplifier for line-level stereo audio signals. It accepts either a balanced or an unbalanced stereo audio signal and delivers a speaker output of 40 watts RMS per channel into 8Ω loads

FEATURES

High Efficiency - Class D operation

Controls - Control knob to adjust volume, bass, middle, treble and balance. Mute and loudness buttons, plus a 10V control port for adjusting the audio gain

USB Port - For firmware update

Flexible Control Options - Front panel, RS-232 (K-Router™ Windows®-based software is included), Ethernet, IR remote (included) and 10KΩ volume level



KRAMER

TECHNICAL SPECIFICATIONS

INPUTS: 1 unbalanced stereo audio on RCA connectors; 1 balanced stereo audio on a 5-pin terminal block connector; 1 USB connector

OUTPUT: 1 speaker stereo audio on a 4-pin terminal block connector

INPUT SENSITIVITY: Unbalanced: 360mVpp; balanced: 220mVpp

MAX. VOLTAGE GAIN: Unbalanced: 35dB; balanced: 40.5dB

OUTPUT POWER: 40W per channel into 8Ω

BANDWIDTH (-3dB): 22kHz

CROSSTALK: <-57dB @20kHz

CONTROLS: Level: <-30dB to 35.5dB; balance: -30dB to 0dB; loudness: -14dB to 0dB @1kHz; bass: -15dB to 12dB @100Hz; mid: -15dB to 11dB @1kHz; treble: -14dB to 13dB @10kHz; input selector buttons, mute button, loudness, bass, mid, treble, balance, volume buttons, IR, RS-232, Ethernet, 10V volume control, 1 USB port for upgrading firmware

COUPLING: Input: AC, output: DC

AUDIO THD + NOISE: 0.15%

AUDIO 2nd HARMONIC: 0.06%

SIGNAL/NOISE RATIO: 63dB, 80dB @10% distortion

AMPLIFIER TYPE: Class D

POWER CONSUMPTION: 24V DC, 2A

INCLUDED ACCESSORIES: Power supply, Windows®-based Kramer control software, IR remote control transmitter

OPTIONS: RK-T2B 19" rack adapter

PRODUCT DIMENSION: 18.75cm x 11.50cm x 2.54cm (7.38" x 4.53" x 1.00") W, D, H

PRODUCT WEIGHT: 0.5kg (1.1lbs) approx

SHIPPING DIMENSION: 35.10cm x 21.20cm x 7.20cm (13.82" x 8.35" x 2.83") W, D, H

SHIPPING WEIGHT: 1.4kg (3.1lbs) approx

