

HTI-A-FB1100

Hitrolink-Feedback Suppressor



Features

- Dual Channel 18-point independent high-speed automatic notch, fast Suppression whistle point.
- Personalization PC Commissioning software, USB drive-free communication mode, easy to operate, handy.
- This machine is equipped with a frequency shift Operating Mode, which is used with a wave trap, and the anti-howling effect is outstanding.

Technical Parameter	
Input Channel	2CH-XLR/TRS
Output Channel	2CH-XLR/TRS
Frequency Response	20HZ-20KHZ
Enter Sensitivity	Sensitivity Adjustable Capacitance/Dynamic Mic Compatible
Input Impedance	20KOHM/600OHM
Output Impedance	20KOHM/100OHM adjustable
Signal-to-noise Ratio (S/N Ratio)	> 105dB
Auto Audio Mixing	AUTO MIX
Frequency division control	High/Low Pass Type/Frequency/Adjustable
Equalization control	12-segment Frequency/Q value/Gain adjustable parameter PEG
Output level	High and low can be switched
Scene settings	12 Scenario Storage Call
Number of trap points	Double 18-segment, static and dynamic Optional
Howl Recognition Speed	Senior High School Low Settable
Operating Mode selection	Test Mode/Run Mode/Pass-Through Mode
Operational language	Chinese/English switchable
Panel lock	Panel Password Lockout
Show	True color TFT at 2.0
Protect	Latency protection against shock during startup and shutdown
Panel control	USB Port, Edit Wheel Settings
Rear panel control	Microphone Sensitivity setting
Consumes power	< 30W
Power source	AC90V-AC240V 50-60HZ International
Operating Temperature	-20°... 85°
Storage temperature	-40°... 85°
Product Dimension	483*226*45MM
Net Weight/Gross Weight	2.8KG/3.2KG