



## TR-92

Dual Audio Transformer

| Speakers



The TR-92 is a 2x100W transformer for speaker signals. The unit takes two 4Ω/8Ω channels from a speaker output of a power amplifier, transforms them to 70/100V and distributes them to an array of loudspeakers

### FEATURES

**Bandwidth** - 18kHz (-3dB)

**Max. Power** - 100 watts

**Passive Device** - No power required

**Desktop Size** - Compact size. 2 units can be rack mounted side-by-side in a 1U rack space with an optional RK-1 adapter



# KRAMER

## TECHNICAL SPECIFICATIONS

INPUTS:	2 low-impedance ( $4\Omega/8\Omega$ ) speaker inputs on terminal block connectors
OUTPUTS:	2 high-impedance speakers on terminal block connectors
MAX POWER:	100W
VOLTAGE GAIN:	7.4dB/10.5dB (70V/100V)
BANDWIDTH (-3dB):	18kHz
OPERATING TEMPERATURE:	0° to +40°C (32° to 104°F)
STORAGE TEMPERATURE:	-10° to +60°C (14° to 140°F)
HUMIDITY:	10% to 90%, RHL non-condensing
OPTIONS:	RK-1 19" rack adapter
PRODUCT DIMENSION:	21.46cm x 16.30cm x 4.36cm (8.45" x 6.42" x 1.72" ) W, D, H
PRODUCT WEIGHT:	2.9kg (6.4lbs) approx
SHIPPING DIMENSION:	35.10cm x 21.20cm x 7.20cm (13.82" x 8.35" x 2.83" ) W, D, H
SHIPPING WEIGHT:	3.5kg (7.7lbs) approx

