

# FS-3000RGUB

USB/SD/FM PLAYER/RECORDER



## DESCRIPTION

USB/SD/FM Player and Mixer

Player, recorder and mixer in one device.

Multitude of playback options and audio inputs/outputs, making it very versatile and adaptable to any installation.

Compact size, occupies only 1 U 19" rack and includes the fixing brackets to the 19" rack cabinet.

Audio inputs and outputs with market standard connections: XLR, jack and RCA.

Distortion-free sound that provides a precise playback of your music.

Allows remote control of the USB/SD/FM player via the remote control.

User-friendly and intuitive.

Ideal for commercial premises, hotels, restaurants, presentations, conference rooms,

## TECHNICAL CHARACTERISTICS



Expand product information on:  
<https://fonestar.com/es/FS-3000RGUB>

<p>FEATURES</p>	<p>USB/SD/FM player and mixer.  Mixer with mic and aux input.  USB/SD recorder/player.  FM Radio  USB/SD memory sticks of 64 GB maximum.  Audio file formats supported MP3, WMA, WAV.  Bass, treble and balance control.  Remote control of the player.</p>
<p>RESPONSE</p>	<p>20-20,000 Hz</p>
<p>CONTROLS</p>	<p>GND lift earth disconnection</p>
<p>INPUTS</p>	<p>1 balanced mic. combo (XLR and 6.3 mm jack)  1 stereo audio, 2 x RCA and 3.5 mm jack  3 aux, 2 x RCA  1 tape in, 2 x RCA</p>
<p>OUTPUTS</p>	<p>1 balanced stereo audio, 2 x XLR  2 stereo audio, 2 x RCA  1 tape out, 2 x RCA  1 stereo headphones, 6.3 mm jack</p>
<p>POWER SUPPLY</p>	<p>230/115 V AC, 7 W</p>
<p>DIMENSIONS</p>	<p>430 x 44.5 x 150 mm depth. 1 U 19" rack</p>
<p>WEIGHT</p>	<p>1.5 kg</p>
<p>ACCESSORIES</p>	<p>Mounts for 19" rack assembly  AM and FM antenna</p>



Expand product information on:  
<https://fonestar.com/es/FS-3000RGUB>