



## RC-3000

Master Programmable Remote Control Panel

---



The **RC-3000** is a programmable remote control for Kramer switchers with RS-232 and RS-485 control. Up to 15 **RC-3000s** can control up to 15 Kramer switchers in a single system.

### FEATURES

---

- **Memory Locations** - Stores up to 8 multiple switches as presets to be recalled and executed when needed.
- **ALL/OFF Controls** - Sends one input to all outputs and can disconnect all outputs or turn off individual outputs.
- **Audio Breakaway Switching.**
- **Flexible Control Options** - Front panel, RS-232 (K-Router™ Windows®-based software is included), RS-485, contact closure & external keyboard up to 128 input/output combinations.
- **Standard 19" Rack Mount Size - 2U.**

TECHNICAL SPECIFICATIONS

- INPUT/OUTPUT: 2 RS-232 IN/OUT on 9-pin D-sub connectors; 1 RS-485 connector on detachable terminal blocks; 9-pole, remote dry contact connector on detachable terminal blocks; 18-pole, keyboard extension connector on detachable terminal blocks.
- SETTING MEMORY: 8 immediate setups for fast access and retrieval.
- CONTROL: Front panel keys, RS-232, RS-485, contact closure switches, external keyboard.
- INDICATORS: Multi-character displays on the front panel.
- POWER CONSUMPTION: 12V DC, 800 mA.
- DIMENSIONS: 19" x 7" x 2U W, D, H, rack mountable.
- WEIGHT: 1.7kg (3.8lbs) approx.
- INCLUDED ACCESSORIES: Power supply, Windows®-based control software.

