



RC-IR1

Infrared Remote Controller



The **RC-IR1** is an infrared wireless remote control for most Kramer RS-232 controllable switchers. The transmitter and receiver can switch up to 96x96 inputs and outputs.

FEATURES

- RC-IR2 Transmitter.
- Receiver - Converts IR input to RS-232 output.
- Memory Locations - Stores up to 99 multiple switches as presets to be recalled and executed when needed.

TECHNICAL SPECIFICATIONS

POWER CONSUMPTION:	Remote control transmitter: AA size regular 1.5V alkaline battery, remote current: 21mA, standby: 5 μ A; external remote receiver: power adapter (12V DC), 28mA maximum.
DIMENSIONS:	Remote control transmitter: 6cm x 3cm x 17cm (2.3" x 1.2" x 6.7") W, D, H; external remote receiver: 8.5cm x 8.5cm x 9.5cm (3.3" x 3.3" x 3.7") W, D, H.
INCLUDED ACCESSORIES:	Remote control transmitter: battery; external remote receiver: attached RS-232 cable and connector; power adapter.