

SI-1VGA

Remote Control Step-In Module Insert

| VGA/UXGA - 15-pin HD



The SI-1VGA is a step-in remote control insert module for VGA and unbalanced stereo audio signals. The module fits into a Kramer TBUS-10 & K-POD301 Podium Table Bus, and is used for remotely taking control of a compatible switcher, such as the VP-81KSi

FEATURES

HDTV Compatible

Remote Step-in Switching - Illuminated button remotely switches the VP-81KSi Easy Installation - Installs in a TBUS-10 & K-POD301, Podium Table Bus



TECHNICAL SPECIFICATIONS

INPUTS: 1 VGA on a 15-pin HD connector, 1 unbalanced stereo audio on a 3.5mm mini

jack

OUTPUTS: 1 VGA on a 15-pin HD connector, 1 unbalanced stereo audio on a 3.5mm mini

jack

CONTROL: Front panel push button

INCLUDED

ACCESSORIES:

M3 x 6mm screws (2) black

PRODUCT

8.90cm x 2.80cm x 2.30cm (3.50" x 1.10" x 0.91") W, D, H

DIMENSION:

PRODUCT WEIGHT: 0.1kg (0.1lbs) approx

SHIPPING

0.00cm x 0.00cm x 0.00cm (0.00" x 0.00" x 0.00") W, D, H

DIMENSION:

SHIPPING WEIGHT: 0.1kg (0.2lbs) approx

