

## VGAA-IN8-F64

8-Channel VGA with Analog Audio Input Card

| Kramer Core



VGAA-IN8-F64 is an eight-channel VGA with analog audio input card for the VS-6464 Series Modular Multi-Format Digital Matrix Switchers. The VGAA-IN8-F64 inputs eight VGA with analog audio signals into the chassis. Audio is accessed by connecting the supplied Kramer VGA with audio cables to each VGA port

## **FEATURES**

Max. Bandwidth - 450MHz **HDTV** Compatible Analog Audio Over Breakaway Connector



## TECHNICAL SPECIFICATIONS

| PORTS:                                     | 8 VGA on 15-pin HD connectors, 8 unbalanced analog audio on 3.5mm mini jack<br>connectors (accessible via C GF/GMAF-30 cables) |
|--|--|
| BANDWIDTH:                                 | 450MHz   |
| MAXIMUM RANGE:                             | 10m (32ft)   |
| POWER<br>CONSUMPTION:                      | 35W  |
| OPERATING<br>TEMPERATURE:                  | 0° to +40°C (32° to 104°F)   |
| STORAGE<br>TEMPERATURE:                    | -40° to +70°C (-40° to 158°F)  |
| HUMIDITY:                                  | 10% to 90%, RHL non-condensing   |
| SAFETY<br>REGULATORY<br>COMPLIANCE:        | CE   |
| ENVIRONMENTAL<br>REGULATORY<br>COMPLIANCE: | Complies with appropriate requirements of RoHs and WEEE  |
| INCLUDED<br>ACCESSORIES:                   | 8 C-GF/GMAF-30 cables  |
| Product Dimensions                         | 39.50cm x 18.00cm x 2.00cm (15.55" x 7.09" x 0.79" ) W, D, H   |
| Product Weight                             | 0.4kg (1.0lbs) approx  |
| Shipping Dimensions                        | 54.80cm x 27.50cm x 10.60cm (21.57" x 10.83" x 4.17" ) W, D, H   |
| Shipping Weight                            | 0.4kg (1.0lbs) approx  |